

Specification Sheet : FHEC30 Series

Project:_

Remarks:

_Type:___

Model No.:

	Rem			
Specification	IS:		Model: FHEC30	
Lamp Type	LED			
Lamp	Red 120VAC, 60Hz, 0 277VAC, 60Hz, 0			
Wattage	Green 120VAC, 60Hz, 0 277VAC, 60Hz, 0		(0) - (0)	
Emergency Operation	90 minutes			
Listings & C	ertifications:			
		6		
		9		
Mechanical	Data:		Standard Features:	
		4.3" 8.2" 4.3"	 Push-to-test Switch LED Charge Indicator Ni-Cad Premium Battery Dual Voltage 120V/277V Universal Mount Long Life Energy Saving LED light source for both exit and emergency heads Field replaceable snap out/in chevron directional indicator. Snap-fit faceplate installs without use of tools Universal single face and double face (extra faceplate included) Fully adjustable glare free lighting heads Universal mounting pattern knockout in backplate for J-box mounting 	

Ordering Information:

Base Model No.	Case Color	Letter Color
FHEC30	W - White	R - Red
FHEC30	B - Black	G - Green

Build part number by adding Base Model No., one of each Case Color, and Letter Color. Example: FHEC30-WR

Fulham Co., Inc extends limited warranty only to the original purchaser or to the first user for the period of **5 years** from the date of manufacture as indicated by the date code stamped on each product and when properly installed and under normal conditions of use, including proper care and charging of batteries. For additional warranty guideline, please refer to our complete product catalog or call customer service at **1-323-599-5000**. DUE TO A PROGRAM OF CONTINUOUS IMPROVEMENT, FULHAM CO., INC RESERVES THE RIGHT TO MAKE ANY VARIATION IN DESIGN OR CONSTRUCTION TO THE EQUIPMENT DESCRIBED. **Address:** 12705 S. Van Ness Ave., Hawthorne, CA 90250 **Website:** www.fulham.com To order this product: **Fax:** 1-323-754-9060 **Email:** order@fulham.com 2011-607 rev